



DENVER VIBRATOR

An American Tradition



IMPORTANT SAFETY INSTRUCTIONS

Rules for safe 4E-180 series generator operation:

Failure to follow these instructions may lead to serious injury or even death.

This equipment is to be operated by trained and qualified personnel only.

Do Not operate this equipment before reading this information.

- **Do not** work alone.
- **Know** how to stop the engine quickly and understand how to operate all of the controls.
- **Check** engine oil level prior to each use and add as necessary before starting engine.
- **Always** wear personal protective clothing, safety glasses and other personal protection devices according to the rules of the work area.
- **Read, understand and follow** any and all brand specific information provided by the particular engine or motor manufacturer.
- **Generators are a source of potentially lethal high voltage** and should be operated by qualified personnel only.
- **Do not** operate electrical equipment standing in water, with wet hands or in the rain. Electrical shock could occur causing bodily harm or even death.
- **Use** adequately sized connecting cable for extension cords.
- **Maintain** electrical cords in good condition and have damage repaired by qualified personnel prior to use. Damaged, frayed or exposed wiring can result in electrical shock causing severe bodily harm or even death.
- **To reduce fire hazards** and provide adequate ventilation keep internal combustion engines at least 3ft (1m) away from buildings, combustible materials and other equipment during operation. Operate the equipment on level or very nearly level surfaces. Do not put the engine powered generator indoors while the engine is still hot.
- **Always** use extreme caution when handling flammable liquids. Fumes are combustible. Always refuel only in a well ventilated area away from sparks and open flame. **Never** refuel a hot or running engine. Fire or explosion could result from fuel vapors or fuel spilled on a hot engine. **Stop** the engine and allow engine to cool before re-fueling. **Do not** smoke around the machine while refueling. **Promptly** clean up any spilled fuel. Failure to follow these recommendations could result in bodily harm or death.
- This generator is equipped with a ground terminal and the **generator must be grounded** to an external grounding source. Ground the generator from the lug provided by the manufacturer according to Federal, State and local codes for site conditions. Failure to properly ground this equipment can result in serious bodily harm or death.
- **Operate** internal combustion engine-driven generators only in well-ventilated areas to avoid deadly carbon monoxide build-up and / or excessive heat due to lack of air flow. This can result in serious bodily harm or even death.
- **Never** operate generator in an explosive atmosphere. This can result in serious bodily harm or death.
- **Check** all tools powered by the generator for proper ground or circuit protection.
- **Always** wear rubber boots and gloves as added protection when operating a concrete vibrator or similar device immersed in a water based solution.

Emergency Preparedness:

- Know the location of the nearest fire extinguisher and first aid kit.
- Know how to contact the nearest ambulance and/or Fire Department

